

Low Profile Single Phase PFC Universal Input Isolated Front End (IFE)

**NON
PLUG**

MODEL	PM3326A-6	PM3327A-6
POWER	1000W	1200W
INPUT	90 to 264VAC	
OUTPUTS	DC	OUTPUT
48V	21A	25A
32V	31A	37A
28V	36A	43A
26V	38A	46A
24V	42A	50A
12V	83A	100A

DIMENSIONS: 3.5" x 5" x 11.25"
(89mm x 127mm x 286mm).
Exclusive of I/O Connectors.

WEIGHT: 10 lbs.

MOUNTING: Mounting holes for 8-32 screws included on the bottom and on one side.

I/O CONNECTORS:

DC Output: DC Terminal Block with 6-32 screws. **AC Input:** Barrier strip with 6-32 screws. DB25 connector for options.



**HOT
PLUG**

MODEL	PM3326AP-6	PM3327AP-6
POWER	1000W	1200W
INPUT	90 to 264VAC	
OUTPUTS	DC	OUTPUT
48V	21A	25A
32V	31A	37A
28V	36A	43A
26V	38A	46A
24V	42A	50A
12V	83A	100A

DIMENSIONS: 3.5" x 5" x 11.5"
(89mm x 127mm x 292mm).
Exclusive of I/O Connectors.

WEIGHT: 10 lbs.

MOUNTING: Designed to lock into matching rack.

I/O CONNECTORS: Elcon Lower Drawer Connector provides hot plug operation.



PMI is the owner of US Patent # 4,677,366 for Power Factor Correction.

FEATURES

- Power Factor Corrected (> 0.99)
- 0°C to +50°C at Full Load
- Output Fully Floating
- Overcurrent Protection
- Overvoltage Protection
- Remote Sense
- Overtemperature Protection
- Self-contained Forced Air Cooling

SPECIFICATIONS

INPUT

RANGE: 90 to 264 VAC.
FREQUENCY: 47 to 63 Hz.
POWER FACTOR: > 0.99 @ Full Load.
HARMONIC CURRENT: < 5%.

OUTPUT

ADJUSTMENT RANGE: +5%/-10% of nominal output voltage.
POLARITY: Output is isolated. It may be referenced plus/minus as required.
REMOTE SENSING: Compensates for up to 0.5V total loop drop in the output line.
STATIC REGULATION:
Line: ±0.25% over full line range.
Load: ±0.25% zero load to full load.
VOLTAGE STABILITY: ±0.1% for 24-hour period after 30-minute warm up.
TEMP COEFFICIENT: ±0.02%/°C from 0°C to +50°C.
P-P RIPPLE AND NOISE: 1% (20 Hz to 50 MHz Bandwidth).
MINIMUM LOAD: Not Required.

TURN ON DELAY: 1 second max from application of AC line.

OVERVOLTAGE PROTECTION: 125% ±5% of nominal. OVP shutdown is latched until the input line is removed for 5 seconds and then reapplied. OVP sensing is done at the output terminals.

OVERCURRENT PROTECTION: Current Limit Point: 105% to 115% of full load.

ENVIRONMENTAL

OVERTEMPERATURE PROTECTION: Automatically shuts down and latches the unit in the event of an overtemperature condition. After cool down, power must be recycled to restart unit.

AUDIBLE NOISE: 50dBA max at 1 meter.
DMTBF: Over 500,000 hours.

TEMPERATURE: Operating: 0°C to +50°C at full load. Storage: -55°C to +85°C.

HUMIDITY: 20% to 95% non-condensing.

ALTITUDE: Operating: 5,000 feet. Derates to 85% at 10,000 feet.
Non-Operating: To 30,000 feet.

VIBRATION: Operating: From 5 to 27 Hz, 0.02 in double amplitude; from 27 Hz to 500 Hz, 0.75G, 3 axes, 3 min per octave sweep, dwell 15 min at resonance.
Non-operating: From 5 to 17 Hz, 0.10 in double amplitude, from 17 to 500 Hz, 1.5G peak; 3 axes, 5 min per octave sweep; dwell 15 min at resonance.

SHOCK: Operating: 5G, half sine, 11msec, 3 axes. Non-Operating: 15G, half sine, 11msec, 3 axes.

COOLING: Forced air, internal fan. Airflow exits at connector end.

EMI: Designed to meet Conducted and Radiated: EN55022 Level A.

SAFETY: Designed to meet UL1950, CSA22.2 No. 950, and TUV to EN60950.

TYPICAL OPTIONS

(Complete Option List Available)

(-1C) AC POWER FAIL: Upon loss of AC line, signal goes from low to high before loss of output regulation.

(-2T) LOGIC INHIBIT: Less than 0.5 volts will inhibit the supply. Two volts or more or an open circuit will enable the supply. Logic inhibit return should be connected to negative output.

(-6B) CURRENT SHARING: Allows two or more similar power supply main outputs to load share using a single wire.

(-8UV) UNDERVOLTAGE DETECT: Signal pulls low when output drops more than 15% ±5% of the nominal. There is no upper trip point. Sensing occurs at the output terminals instead of the remote sense leads. High good (LED on) and Low bad (LED off).

(-20C) ISOLATION DIODE: Built-in Oring diodes in the positive output line to prevent a failed power supply from affecting the bus.

(-33) CURRENT MONITOR: The current monitor signal is referenced to the negative output. It is accurate to within +/-10%, from 10% to 100% load. The analog signal 0V to 5V is proportional to the load when increased from no load to maximum load.

NOTE: The option signals (-1C) and (-2T) are floating and referenced to Logic Return. Logic Return should be connected by the customer to the system common.

SPECIAL OPTION

Intelligent Power Supply



- Built-in microchip controls all power supply & battery parameters, plus stores data on history, operating conditions & address.
- Allows user to program system functions & alarms.
- Permits either local monitoring (via RS485 bus) or remote monitoring (via modem).

SPECIFIC APPLICATIONS

- Telecom and Datacom
- Computer / Network Systems
- Broadcast

